FLEXIDOME IP outdoor 4000 HD

www.boschsecurity.com















- ▶ Outdoor IP dome camera with varifocal lens
- ▶ 720p resolution for sharp images
- ► Fully configurable quad streaming
- ► Regions of interest and E-PTZ
- ▶ IR version with 15 m (50 ft) viewing distance

The HD indoor dome cameras from Bosch are professional surveillance cameras that provide high quality HD images for demanding security and surveillance network requirements. These domes are true day/night cameras offering excellent performance day or night.

There is a version with a built-in active infrared illuminator that provides high performance in extreme low-light environments.

System overview

Vandal resistant outdoor dome with varifocal lens Ideal for outdoor use, the IK10-rated design is suitable for installations where a vandal resistance is important. The camera is protected against water and dust to IP66 standards. The varifocal lens allows you to choose the coverage area to best suit your application. Mounting options are numerous, including surface, wall, and suspended-ceiling mounting.

Functions

Intelligent Dynamic Noise Reduction reduces bandwidth and storage requirements

The camera uses Intelligent Dynamic Noise Reduction which actively analyzes the contents of a scene and reduces noise artifacts accordingly.

The low-noise image and the efficient H.264 compression technology provide clear images while reducing bandwidth and storage by up to 50% compared to other H.264 cameras. This results in reduced-bandwidth streams that still retain a high image quality and smooth motion. The camera provides the most usable image possible by cleverly optimizing the detail-to-bandwidth ratio.

Area-based encoding

Area-based encoding is another feature which reduces bandwidth. Compression parameters for up to eight user-definable regions can be set. This allows uninteresting regions to be highly compressed, leaving more bandwidth for important parts of the scene.

Bitrate optimized profile

The average typical optimized bandwidth in kbits/s for various image rates is shown in the table:

fps	720p	480p
30	1200	600
15	955	478
12	877	438

5	568	284
2	245	122

Multiple streams

The innovative multi-streaming feature delivers various H.264 streams together with an M-JPEG stream. These streams facilitate bandwidth-efficient viewing and recording as well as integration with third-party video management systems.

Depending on the resolution and frame rate selected for the first stream, the second stream provides a copy of the first stream or a lower resolution stream. The third stream uses the I-frames of the first stream for recording; the fourth stream shows a JPEG image at a maximum of 10 Mbit/s.

Regions of interest and E-PTZ

Regions of Interest (ROI) can be user defined. The remote E-PTZ (Electronic Pan, Tilt and Zoom) controls allow you to select specific areas of the parent image. These regions produce separate streams for remote viewing and recording. These streams, together with the main stream, allow the operator to separately monitor the most interesting part of a scene while still retaining situational awareness.

Two-way audio and audio alarm

Two-way audio allows the operator to communicate with visitors or intruders via an external audio line input and output. Audio detection can be used to generate an alarm if needed.

Tamper and motion detection

A wide range of configuration options is available for alarms signaling camera tampering. A built-in algorithm for detecting movement in the video can also be used for alarm signaling.

Storage management

Recording management can be controlled by the Bosch Video Recording Manager (VRM) or the camera can use iSCSI targets directly without any recording software.

Edge recording

The MicroSD card slot supports up to 2 TB of storage capacity. A microSD card can be used for local alarm recording. Pre-alarm recording in RAM reduces recording bandwidth on the network, or — if microSD card recording is used — extends the effective life of the storage medium.

Cloud-based services

The camera supports time-based or alarm-based JPEG posting to four different accounts. These accounts can address FTP servers or cloud-based storage facilities (for example, Dropbox). Video clips or JPEG images can also be exported to these accounts.

Alarms can be set up to trigger an e-mail or SMS notification so you are always aware of abnormal events.

Easy installation

Power for the camera can be supplied via a Power-over-Ethernet compliant network cable connection. With this configuration, only a single cable connection is required to view, power, and control the camera. Using PoE makes installation easier and more cost-effective, as cameras do not require a local power source.

The camera can also be supplied with power from +12 VDC power supplies.

For trouble-free network cabling, the camera supports Auto-MDIX which allows the use of straight or crossover cables.

True day/night switching

The camera incorporates mechanical filter technology for vivid daytime color and exceptional night-time imaging while maintaining sharp focus under all lighting conditions.

Hybrid mode

An analog video output enables the camera to operate in hybrid mode. This mode provides simultaneous high resolution HD video streaming and an analog video output via an SMB connector. The hybrid functionality offers an easy migration path from legacy CCTV to a modern IP-based system.

Access security

Password protection with three levels and 802.1x authentication is supported. To secure Web browser access, use HTTPS with a SSL certificate stored in the camera. The video and audio communication channels can be independently AES encrypted with 128-bit keys by installing the optional encryption site license.

Complete viewing software

There are many ways to access the camera's features: using a web browser, with the Bosch Video Management System, with the free-of-charge Bosch Video Client or Video Security Client, with the video security mobile app, or via third-party software.

Video security App

The Bosch video security mobile App has been developed to enable **Anywhere** access to HD surveillance images allowing you to view live images from any location. The App is designed to give you complete control of all your cameras, from panning and tilting to zoom and focus functions. It's like taking your control room with you.

This App, together with the separately available Bosch transcoder, will allow you to fully utilize our dynamic transcoding features so you can play back images even over low-bandwidth connections.

System integration

The camera conforms to the ONVIF Profile S specification. Compliance with this standard guarantees interoperability between network video products regardless of manufacturer.

Third-party integrators can easily access the internal feature set of the camera for integration into large projects. Visit the Bosch Integration Partner Program (IPP) website (ipp.boschsecurity.com) for more information.

Certifications and approvals

HD standards

Complies with the SMPTE 296M-2001 Standard in:

- Resolution: 1280x720

- Scan: Progressive

- Color representation: complies with ITU-R BT.709


- Aspect ratio: 16:9

- Frame rate: 25 and 30 frames/s

Standards	IEC 62471 (IR version)
	EN 60950-1
	UL 60950-1
	UL 60950-22
	CAN/CSA-C22.2 NO. 60950-1-03
	CAN/CSA-C22.2 NO. 60950-22
	EN 50130-4
	EN 50130-5
	FCC Part15 Subpart B, Class B
	EMC directive 2004/108/EC
	EN 55022 class B
	EN 55024
	AS/NZS CISPR 22 (equal to CISPR 22)
	ICES-003 Class B
	VCCI J55022 V2/V3
	EN 50121-4
	EN 60950-22
ONVIF compliance	EN 50132-5-2; IEC 62676-2-3
Product certifications	CE, FCC, UL, cUL, RCM, CB, VCCI
Ingress protection	IP66
Impact protection	IK10

Region	Certification	
Europe	CE	Outdoor 4000_5000
USA	UL	Outdoor 4000_5000

Installation/configuration notes



Dimensions mm (inch)

Parts included

• Camera

With IR

- · Screw kit
- Desiccant
- · Conduit adapter kit
- · Installation documentation

Technical specifications

recimical specifications		
Power		
Input voltage	+12 VDC or Power-over-Ethernet (48 VDC nominal)	
Power consumption	3.8 W max. 6.3 W max. (IR version)	
PoE	IEEE 802.3af (802.3at Type 1) Power level: Class 2	
Sensor		
Sensor type	1/2.7-inch CMOS	
Active pixels	1280 x 960	
Video performance - Sensitivity		
Sensitivity – (3200K, reflectivity 89%, F1.5, 30IRE)		
Color	0.24 lx	
Mono	0.05 lx	

0.0 lx

Video performance - Dyi		
Dynamic range	76 dB	
Video streaming		
Video compression	H.264 (MP); M-JPEG	
Streaming	Multiple configurable streams in H.264 and M- JPEG, configurable frame rate and bandwidth. Regions of Interest (ROI)	
Overall IP Delay	Min. 120 ms, Max. 340 ms	
GOP structure	IP, IBP, IBBP	
Encoding interval	1 to 25 [30] ips	
Encoder regions	Eight independent areas for setting encoder quality to optimize bitrate.	
Video resolution (H x V)		
720p HD	1280 x 720	
1.3 MP (4:3)	1280 x 960	
Upright 9:16 (cropped)	400 x 720	
D1 4:3 (downscaled/cropped)	704 x 480	
480p SD	Encoding: 704 x 480; Displayed: 854 x 480	
432p SD	768 x 432	
288p SD	512 x 288	
240p SD	Encoding: 352 x 240; Displayed: 432 x 240	
144p SD	256 x 144	
Video functions		
Day/Night	Color, Monochrome, Auto	
Adjustable picture settings	Contrast, Saturation, Brightness	
White Balance	4 automatic modes, manual mode and measure	
Shutter	Automatic Electronic Shutter (AES); Fixed (1/12 to 1/15000) selectable; Default shutter	
Backlight compensation	On/off	
Noise reduction	Intelligent Dynamic Noise Reduction with separate temporal and spatial adjustments	
Contrast enhancement	On/off	
Sharpness	Sharpness enhancement level selectable	

Video functions		
Intelligent defog	Intelligent Defog automatically adjusts parameters for best picture in foggy or misty scenes (switchable)	
Privacy Masking	Eight independent areas, fully programmable	
Video Analysis	MOTION+	
Other functions	Image mirror, Image flip, Pixel counter, Video watermarking, Display stamping, Scene modes, Location	
Night vision (IR version only)		
Distance	15 m (50 ft)	
LED	10 LED high efficiency array, 850 nm	
IR intensity	Adjustable	
Optical		
Lens type	Varifocal 3.3 to 10 mm, DC Iris F1.5 – 360, IR corrected	
Lens mount	Board mounted	
Day/Night	Switched mechanical IR filter	
Horizontal field of view	35.3° - 105.5°	
Vertical field of view	19.7° - 55.4°	
Input/output		
Analog video out	SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm	
Analog video out Audio line in		
-	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack	
Audio line in	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack connector	
Audio line in Audio line out	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack connector 0.707 Vrms at 16 Ohm typical, jack connector	
Audio line in Audio line out Alarm input Alarm input	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack connector 0.707 Vrms at 16 Ohm typical, jack connector 1 input	
Audio line in Audio line out Alarm input Alarm input activation	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack connector 0.707 Vrms at 16 Ohm typical, jack connector 1 input Short or DC 5V activation	
Audio line in Audio line out Alarm input Alarm input activation Alarm output	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack connector 0.707 Vrms at 16 Ohm typical, jack connector 1 input Short or DC 5V activation 1 output	
Audio line in Audio line out Alarm input Alarm input activation Alarm output Alarm output voltage	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack connector 0.707 Vrms at 16 Ohm typical, jack connector 1 input Short or DC 5V activation 1 output 30 VDC, max. load 0.5 A	
Audio line in Audio line out Alarm input Alarm input activation Alarm output Alarm output voltage Ethernet	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack connector 0.707 Vrms at 16 Ohm typical, jack connector 1 input Short or DC 5V activation 1 output 30 VDC, max. load 0.5 A	
Audio line in Audio line out Alarm input Alarm input activation Alarm output Alarm output voltage Ethernet Audio streaming	75 Ohm 0.707 Vrms max, 10 kOhm typical, jack connector 0.707 Vrms at 16 Ohm typical, jack connector 1 input Short or DC 5V activation 1 output 30 VDC, max. load 0.5 A RJ45 G.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate	

Local storage	
Internal RAM	10 s pre-alarm recording
Memory card slot	Supports up to 32 GB microSDHC / 2 TB microSDXC card. (An SD card of Class 6 or higher is recommended for HD recording)
Recording	Continuous recording, ring recording. alarm/ events/schedule recording
Software	
Unit discovery	IP Helper
Unit configuration	Via web browser or Configuration Manager
Firmware update	Remotely programmable
Software viewing	Web browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party software
Latest firmware and software	http://downloadstore.boschsecurity.com/
Network	
Protocols	IPv4, IPv6, UDP, TCP, HTTP, HTTPS, RTP/ RTCP, IGMP V2/V3, ICMP, ICMPv6, RTSP, FTP, Telnet, ARP, DHCP, APIPA (Auto-IP, link local address), NTP (SNTP), SNMP (V1, MIB- II), 802.1x, DNS, DNSv6, DDNS (DynDNS.org, selfHOST.de, no-ip.com), SMTP, iSCSI, UPnP (SSDP), DiffServ (QoS), LLDP, SOAP, Dropbox, CHAP, digest authentication
Encryption	TLS 1.0, SSL, DES, 3DES
Ethernet	10/100 Base-T, auto-sensing, half/full duplex
Connectivity	Auto-MDIX
Interoperability	ONVIF Profile S; GB/T 28181
Mechanical	
3-axis adjustment (pan/tilt/rotation)	350° / 130° / 330°
Dimensions	Diameter: 145 mm (5.71 in) Height: 131 mm (5.14 in)
Weight	1102 g (2.43 lb) approx.
Color	RAL 9004, RAL 9010

Environmental	
Operating temperature	-30 °C to +50 °C (-22 °F to +122 °F)
Storage temperature	-30 °C to +70 °C (-22 °F to +158 °F)
Humidity	20% to 90% relative humidity (non condensing)

Ordering information

FLEXIDOME IP outdoor 4000 HD

Vandal-resistant IP dome camera for outdoor HD surveillance. Varifocal 3.3 to 10 mm f1.5 lens; IP66; IK10; IDNR; day/night; H.264 quad-streaming; cloud services; motion/tamper/audio detection; 720p Order number NDN-41012-V3

FLEXIDOME IP outdoor 4000 IR

Vandal-resistant IP dome camera for outdoor HD surveillance. Varifocal 3.3 to 10 mm f1.5 lens; IP66; IK10; IDNR; day/night; H.264 quad-streaming; cloud services; motion/tamper/audio detection; 720p; infrared

Order number NDI-41012-V3

Accessories

NDA-LWMT-DOME Dome Wall Mount

Sturdy wall L-shaped bracket for dome cameras Order number NDA-LWMT-DOME

VDA-WMT-AODOME Outdoor Wall Mount

Sturdy outdoor wall mount bracket for dome cameras (Ø166 mm)

Order number VDA-WMT-AODOME

VDA-PMT-AODOME Outdoor Pipe Mount

Sturdy outdoor pipe mount bracket for dome cameras (Ø166 mm)

Order number VDA-PMT-AODOME

LTC 9213/01 Pole Mount Adapter

Flexible pole mount adapter for camera mounts (use together with the appropriate wall mount bracket). Max. 9 kg (20 lb); 3 to 15 inch diameter pole; stainless steel straps

Order number LTC 9213/01

NDA-FMT-DOME In-ceiling mount

In-ceiling flush mounting kit Order number NDA-FMT-DOME

NDA-ADT4S-MINDOME 4S Surface Mount Box

Surface mount box (\emptyset 145 mm / \emptyset 5.71 in) for dome cameras (use together with the appropriate dome adapter bracket).

Order number NDA-ADT4S-MINDOME

Monitor/DVR Cable SMB 0.3M

0.3 m (1 ft) analog cable, SMB (female) to BNC (female) to connect camera to coaxial cable Order number NBN-MCSMB-03M

Monitor/DVR Cable SMB 3.0M

3 m (9 ft) analog cable, SMB (female) to BNC (male) to connect camera to monitor or DVR Order number NBN-MCSMB-30M

IP66 I/O Cable

An IP66 certified cable for easy waterproof installation Order number NDN-IOC-30M

Represented by:

Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 security.sales@us.bosch.com www.boschsecurity.us

Europe, Middle East, Africa: Bosch Security Systems B.V. Boscn Security Systems B.V. P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: +31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com

www.boschsecurity.com

Asia-Pacific: Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2699 apr.securitysystems@bosch.com www.boschsecurity.asia

China: America Latina:
Bosch (Shanghai) Security Systems Ltd. Robert Bosch Ltda Security Systems Division
203 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone: +55 19 2103 2860
Phone +86 21 22181111
Fax: +55 19 2103 2862
Interpretable Phone Ph Fax: +86 21 22182398 www.boschsecurity.com.cn

latam.boschsecurity@bosch.com www.boschsecurity.com